





## PMC6


If you are a professional who needs the last word in reliable reference monitoring in a compact form, then the PMC6 active two-way is the answer. Packed with innovation and providing the same sonic signature as our renowned larger monitors, it's ideal for smaller control rooms or for use in larger immersive systems, where its astounding resolution allows critical mix decisions to be made with absolute confidence.

With 20mm of excursion, the bespoke 6-inch bass driver is designed specifically to integrate with our latest ATL™ bass-loading and Laminair™ airflow technologies. The combination outperforms most 8-inch monitors, offering unparalleled bass extension, headroom, dynamics, and low distortion at all levels. The high end is courtesy of a one-inch precision-built fabric soft-dome tweeter, with a shallow waveguide that creates wide, tonally consistent dispersion and rock-solid imaging. Both the bass and treble drivers are precisely and individually controlled by a pair of 200W ultra-low-distortion, high-damping-factor Class-D amplifiers.


Whether in portrait or landscape placement, the PMC6's sophisticated DSP engine automatically adjusts the crossover, ensuring optimum tonal accuracy, phase and imaging.

The monitor can be calibrated using the rear-panel controls or with PMC's intuitive browser-accessible SoundAlign software.

The PMC6 can be upgraded by adding a PMC8 SUB to create a full-range, free-standing PMC6 XBD system. Activating the 'XBD' DSP mode ensures the perfect marriage of the two units, creating a clean LF extension down to 25Hz.











PMC6 (right landscape)

## **SPECIFICATIONS**



Туре	Active 2-way nearfield reference monitor with ATL™ bass loading
Drive unit complement	<b>LF</b> PMC 150mm (6") studio 6 driver
	HF PMC 27mm (1") soft dome tweeter
Effective ATL™ length	1.8m (5.9ft)
Frequency response	39Hz - 25kHz (- 3dB) (@1m full space, on-axis)
Sensitivity	+4dBu input signal = 98dB SPL @ 1m
Max continuous SPL	106dB @1m (Half space value calculated as +3dB from full space measurement. Unweighted input, 20-20kHz Pink Noise (IEC) with 12dB CF for 2 hours AES2-1984 duration)
Max Peak SPL	118dB @1m (Half space value calculated as +3dB from full space measurement. Unweighted input, 20-20kHz Pink Noise (IEC) with 12dB CF for 2 hours AES2-1984 duration)
Directivity	<b>H</b> +/-60 degrees <b>V</b> +50/-40 degrees (-6dB off axis @10kHz)
Input	XLR switchable between analogue & digital AES3
	Analogue input - +20/+24dBu max. input level (selectable) - 22K ohm input impedance
	Digital input - 16/24-bit AES3 signal, left, right or left + right - 18 - 192kHz sample rate - 110 ohm input impedance
	Expansion card slot - For future connectivity upgrades
Output	XLR digital AES3 (fixed 24-bit @ 96kHz)
Network	RJ45 for use with PMC SoundAlign web interface
	RJ45 for use with PMC SoundAlign web interface  Level Trim (+/-10dB) Orientation (portrait, landscape, auto) High-pass filter (20 - 200Hz, 12dB/Oct) Delay (0 - 30mS) Phase (normal or inverted) LF & HF shelving filters (20Hz - 20kHz, +/- 10dB, Q 0.707) Parametric EQ (5 bands, 20Hz - 20kHz, +/- 10dB) User presets (3 + factory defaults)
Network	Level Trim (+/-10dB) Orientation (portrait, landscape, auto) High-pass filter (20 - 200Hz, 12dB/Oct) Delay (0 - 30mS) Phase (normal or inverted) LF & HF shelving filters (20Hz - 20kHz, +/- 10dB, Q 0.707) Parametric EQ (5 bands, 20Hz - 20kHz, +/- 10dB)
Network Features	Level Trim (+/-10dB) Orientation (portrait, landscape, auto) High-pass filter (20 - 200Hz, 12dB/Oct) Delay (0 - 30mS) Phase (normal or inverted) LF & HF shelving filters (20Hz - 20kHz, +/- 10dB, Q 0.707) Parametric EQ (5 bands, 20Hz - 20kHz, +/- 10dB) User presets (3 + factory defaults)
Network Features Latency	Level Trim (+/-10dB) Orientation (portrait, landscape, auto) High-pass filter (20 - 200Hz, 12dB/Oct) Delay (0 - 30mS) Phase (normal or inverted) LF & HF shelving filters (20Hz - 20kHz, +/- 10dB, Q 0.707) Parametric EQ (5 bands, 20Hz - 20kHz, +/- 10dB) User presets (3 + factory defaults) 2.4mS
Network Features  Latency Amplifier power per channel	Level Trim (+/-10dB) Orientation (portrait, landscape, auto) High-pass filter (20 - 200Hz, 12dB/Oct) Delay (0 - 30mS) Phase (normal or inverted) LF & HF shelving filters (20Hz - 20kHz, +/- 10dB, Q 0.707) Parametric EQ (5 bands, 20Hz - 20kHz, +/- 10dB) User presets (3 + factory defaults) 2.4mS  LF 1 x 200Wrms  HF 1 x 200Wrms
Network Features  Latency Amplifier power per channel Mains	Level Trim (+/-10dB) Orientation (portrait, landscape, auto) High-pass filter (20 - 200Hz, 12dB/Oct) Delay (0 - 30mS) Phase (normal or inverted) LF & HF shelving filters (20Hz - 20kHz, +/- 10dB, Q 0.707) Parametric EQ (5 bands, 20Hz - 20kHz, +/- 10dB) User presets (3 + factory defaults) 2.4mS  LF 1 x 200Wrms  HF 1 x 200Wrms 100 - 240VAC auto-switching, 50-60Hz (IEC C14)
Network Features  Latency Amplifier power per channel Mains Power consumption (idle)	Level Trim (+/-10dB) Orientation (portrait, landscape, auto) High-pass filter (20 - 200Hz, 12dB/Oct) Delay (0 - 30mS) Phase (normal or inverted) LF & HF shelving filters (20Hz - 20kHz, +/- 10dB, Q 0.707) Parametric EQ (5 bands, 20Hz - 20kHz, +/- 10dB) User presets (3 + factory defaults) 2.4mS  LF 1 x 200Wrms  HF 1 x 200Wrms 100 - 240VAC auto-switching, 50-60Hz (IEC C14) 35W
Network Features  Latency Amplifier power per channel Mains Power consumption (idle) Power consumption (max)	Level Trim (+/-10dB) Orientation (portrait, landscape, auto) High-pass filter (20 - 200Hz, 12dB/Oct) Delay (0 - 30mS) Phase (normal or inverted) LF & HF shelving filters (20Hz - 20kHz, +/- 10dB, Q 0.707) Parametric EQ (5 bands, 20Hz - 20kHz, +/- 10dB) User presets (3 + factory defaults) 2.4mS  LF 1 x 200Wrms HF 1 x 200Wrms 100 - 240VAC auto-switching, 50-60Hz (IEC C14) 35W 400W H 400mm (15.7") W 215mm (8.5") D 372mm (14.6") (portrait)

